

Specifications

General Specifications

Product Name	PowerBank 7.5K Li-Ion Rechargeable Battery
Model Number	E-18 Plus
Dimensions	Length: 91 mm Width: 52.3 mm Height: 19.5 mm
Weight	165 g
Available Colors	Gold, Pink, Grey
Country of Origin	Taiwan

Input and Output Specifications

Port	Charging Input	Discharging Output	Remark
Micro USB	DC 5V / 2A	N/A	
Type-C	DC 5V / 2A	5V / 3A	
USB	N/A	DC 5V / 2.4A	Output above 5V supports only for products with QC 3.0 quick charge mode

*Do not charge devices with both Type-C and USB ports simultaneously

Effective Capacity

Cell Capacity	3.7V / 7500mAh
Rating Capacity	4950mAh

Protections and Features

- Over-charge current protection
- Over-charge voltage protection
- Over-discharge current protection
- Over-discharge voltage protection
- Short-circuit protection
- Sleep mode

Compatible Devices

- Tablet: iPad series and other 5V/2.4A high-charging current tablets
- Phone: iPhone, ASUS, HTC, Nokia, Motorola, LG, Sony, Samsung, Xiaomi all series
- Other devices that use USB or USB-C port charging

Operation Instructions

To use the LED flashlight

- Press and hold the POWER for 2 seconds to turn it ON
- To turn it OFF, press and hold the POWER for 2 seconds

To CHARGE the GTS PowerBank 7K

- Use the included cable or certified cable to connect a DC 5V / 1.5A power source to the corresponding charging port on the GTS PowerBank 7.5K
- Charging should start automatically
- Charging time is approximately 5 hours
- Charging is complete when all LED's are continuously on

To USE the GTS PowerBank 7K to charge other devices

- Use the included cable or certified cable to connect a DC 5V / 1.5A power source to the corresponding output port on the GTS PowerBank 7.5K.
- Press the POWER button to turn on the LED indicators and charge the connected device. Refer to the "LED Indication" section for details.
- Press the POWER button again to turn off the LED indicators and stop charging the connected device.

LED Indication

- LED Indication when charging the GTS PowerBank 7.5K:

Status	LED1	LED2	LED3	LED4
Charging	Flash according to the charged power level			
Charging Completed	On	On	On	On

- LED Indication when charging a device using the GTS PowerBank 7.5K:

Press the **POWER** button to charge a device and turn on LED indicators.

GTS PowerBank 10K Remaining power level	LED1	LED2	LED3	LED4
100% - 75%	On	On	On	On
75% - 50%	On	On	On	Off
50% - 25%	On	On	Off	Off
25% - 5%	On	Off	Off	Off
5% - 0%	Flash	Off	Off	Off

Guidelines and Warnings

1. Do NOT charge to and discharge from the GTS PowerBank 7.5K simultaneously.
2. Use only the included cable or certified cable to charge the GTS PowerBank 7.5K.
3. Please charge the GTS PowerBank 7.5K when LED1 starts flashing to recover it from low power level. Keeping the GTS PowerBank 7.5K at low power level for an extended period of time may reduce its useful life and optimal performance.
4. Please remove the charging cable when charging is complete. Do NOT charge the GTS PowerBank 7.5K more than 10 hours at a time.
5. When unused, please fully charge the GTS PowerBank 7.5K every 3 months to maintain its useful life and optimal performance.
6. Input current limit should not exceed 2.4A.
7. Do NOT short-circuit the GTS PowerBank 7.5K.
8. Do NOT disassemble the GTS PowerBank 7.5K.
9. Do NOT expose the GTS PowerBank 7.5K to an environment above 40°C (104°F) or below 0°C (32°F).
10. Do NOT expose the GTS PowerBank 7.5K to moisture or direct sunlight.
11. The GTS PowerBank 7.5K may explode if disposed of in fire.

ABOUT US

Global Technology Systems, Inc. (“GTS”) is the trusted expert in mobile power technology. GTS designs and manufactures high-performance batteries, chargers, and power management technologies for essential mobile devices. Millions of public safety, government, military, and business professionals rely on GTS to power mission critical communications and mobile computing applications. Founded in 2000, GTS is headquartered in Framingham, Massachusetts.

